


INSTALLATION INSTRUCTIONS

USA

ORION SERIES LED'S

ORION ARA 12

ART. NO.	135 601-1/c	clear, LED white	135 603/c	clear, LED green
	135 601-1/f	frosted, LED white	135 603/f	frosted, LED green
	135 601/c	clear, LED white	135 604/c	clear, LED red
	135 601/f	frosted, LED white	135 604/f	frosted, LED red
	135 602/c	clear, LED blue	135 605/c	clear, LED amber
	135 602/f	frosted, LED blue	135 605/f	frosted, LED amber



IMPORTANT SAFETY INSTRUCTIONS



1. THIS PRODUCT MUST BE INSTALLED BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED, IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE.
2. Fixture must be wired to a 12VAC transformer capable of 1.5W max.
3. Dimming must be done on the primary side of the transformer.
4. Fixture should only be installed in indoor dry locations.
5. Turn off power prior to any work on the systems.
6. Warranty is void in case of unauthorized modifications and/ or improper use.

READ ALL OF THESE INSTALLATION INSTRUCTIONS BEFORE INSTALLING THE FIXTURE

Contents of Delivery:
 ORION ARA 12 - qty. (1)
 Plastic Anchor - qty.(1)

- Step1
 - Drill a 1-7/8" hole into the mounting surface.
- Step2
 - Insert the plastic anchor (A) into the cutout. The anchor should fit tightly in the hole and be flush with the mounting surface (tap lightly with a hammer if necessary).
- Step3
 - Strip 1/4" off sleeve and connect the low-voltage wires (B) from the transformer to the terminal block (C) and tighten screws securely.
- Step4
 - Insert the ORION ARA12 (D) into the plastic anchor (A) until flush and secure.

